


Product data sheet

Radio switch: 1way, 2-pole (set)



Reference number

RJ-314

Radio switch: 1way, 2-pole, with frame (Epsilon Slim line)

RJ-314 set includes 2 products: transmitter - DJ-01s and radio receiver DJ-01i, battery
DJ-01s transmitter could be used in flush and surface mounting
the set gives comfortable solution used to control lighting and other receivers remotely

PRODUCT FUNCTIONAL FEATURES:

- complete set of wireless control (2-channel button radio transmitter DJ-01s and 1-channel bistable radio receiver DJ-01i)
- five operation modes: switching on mode, switching off, monostable, bistable, time- (switch off delay)
- low current consumption, possibility of constant work
- light operation control and other receivers control
- wide range of operation (up to 180m)
- possibility of widening operation range by means of RTN-01 retransmitter (produced by Zamel)
- receivers are easily installed in an electric-light fitting or in Ø60 mm junction box (DIN 49073)
- operation is optically signalled

Centre plates colour, EAN code:

E/B - White, 4770025876091
E/S - Sandy, 4770025876107
E/R - Brown, 4770025963609
E/Mt - Metallic, 4770025876114
E/J - Black, 4770025876121
E/Ch - Champagne, 4770025876138

Technical specifications:

Transmitter:	
Rated supply voltage	3V
Battery type	CR2032
Battery life	from 3 to 5 years
Number of channels	2
Number of channels receiver	1
Frequency transmission (radio)	868, MHz
Transmission method	one-way
Maximum range in open area	250m.
Maximum range in the open area of the receiver	230m.
Maximum number of transmitters	5
Set time from	1s.
Receiver:	
Input voltage, frequency	AC 250 V +- 10% , 50/60 Hz
Parameters of relay contacts	1NO/NC 5A / 250V AC AC1 1250 VA
Number of connection terminals / cables	5
Working position	free
Fixing the housing	expansion pin, adhesive tape
Protection degree	IP20