


# Product data sheet



## 2-channel button radio transmitter



### Reference number

DJ-01s

### Radio switch button: 2-channel, with frame

includes: transmitter DJ-01s, battery, frame (Epsilon Slim line)

could be used in flush and surface mounting

the set gives comfortable solution used to control lighting and other receivers remotely

### PRODUCT FUNCTIONAL FEATURES:

- five operation modes: switching on mode, switching off, monostable, bistable, time- (switch off delay)
- low current consumption, possibility of constant work
- light operation control and other receivers control
- wide range of operation (up to 180m)
- possibility of widening operation range by means of RTN-01 retransmitter (produced by Zamel)
- operation is optically signalled

### Centre plates colour, EAN code:

E/B - White, 4770025960417

E/S - Sandy, 4770025960431

E/R - Brown, 4770025963586

E/Mt - Metallic, 4770025960455

E/J - Black, 4770025960479

E/Ch - Champagne, 4770025960493

### Technical specifications:

#### Transmitter:

Rated supply voltage	3V
Battery type	CR2032
Battery life	from 3 to 5 years
Number of channels	2
Number of channels receiver	1
Frequency transmission (radio)	868, MHz
Transmission method	one-way
Maximum range in open area	250m.
Maximum range in the open area of the receiver	230m.
Maximum number of transmitters	5
Set time from	1s.
Fixing the housing	expansion pin, adhesive tape
Protection degree	IP20